Please download the latest datasheet of BNX022-01# from the official website of Murata Manufacturing Co., Ltd.

Note: This datasheet may be out of date.

http://www.murata.com/en-gb/products/productdetail?partno=BNX022-01%23

"#" indicates a package specification code.










< List of part numbers with package codes > BNX022-01K BNX022-01L BNX022-01B



Appearance & Shape








Packaging Information

Packaging	Specifications	Minimum Order Quantity
K	330mm Embossed Tape	1500
L	180mm Embossed Tape	400
В	Bulk(Bag)	100



Other Usage For general

1 of 4

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.



BNX022-01#

Note: This datasheet may be out of date.

Please download the latest datasheet of BNX022-01# from the official website of Murata

Manufacturing Co., Ltd.

http://www.murata.com/en-gb/products/productdetail?partno=BNX022-01%23

"#" indicates a package specification code.



BNX02□ series is SMD type high performance and provides excellent noise suppression on DC power lines.

Features

- 1. Large rated current (10A-15A)
- 2. Supporting wide frequency range From 15kHz to 1GHz:35dB min.(BNX029)
- 3. Mounting area and volume is reduced.
- 4. Effective for impulse noise such as electrostatic discharge or spike noise.

Applications

- 1. Displays (PDP/LCD-TV)
- 2. Digital AV equipment
- 3. Amusement equipment
- 4. PC peripheral equipment
- Industry equipment, measurement equipment, power supplies

2 of 4

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering





BNX022-01#

Note: This datasheet may be out of date.

Please download the latest datasheet of BNX022-01# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-gb/products/productdetail?partno=BNX022-01%23

"#" indicates a package specification code.



Specifications

Shape	SMD	
Length	12.1mm	
Length Tolerance	±0.2mm	
Width	9.1mm	
Width Tolerance	±0.2mm	
Thickness	3.1mm	
Thickness Tolerance	±0.2mm	
Rated Current	20A	
Operating Temperature Range	-40°C to 125°C	
Mass(typ.)	0.8g	
Rated Voltage	50Vdc	
Withstanding Voltage	125Vdc	
Insulation Resistance(min.)	500ΜΩ	
Insertion Loss	1MHz to 1GHz:35dB min. (Line impedance=50Ω)	

3 of 4

Attention

1.This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.




BNX022-01#


Note: This datasheet may be out of date.


Please download the latest datasheet of BNX022-01# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-gb/products/productdetail?partno=BNX022-01%23

"#" indicates a package specification code.








Insertion Loss Characteristics

In operating temperature exceeding +85°C, derating of current is necessary for BNX022/023/029/024H/025H/ $\ensuremath{\text{026H/027H}}$ series. Please apply the derating curve shown in chart according to the operating temperature.

Derating of Rated Current



Equivalent Circuit

Derating of Rated Current

4 of 4

Attention

- 1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.
- 2. This datasheet has only typical specifications because there is no space for detailed specifications.
- Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.

